

HIGH POWER / AUXILIARY EQUIPMENT / AUDIO DISTRIBUTORS

FDT-110F

AUDIO SPLITTER



- ✓ Converts 1 mono signal to 10 mono outputs
- ✓ Independent volume controls per output
- ✓ Balanced inputs and outputs
- ✓ Ideal for sound systems, press splitters etc.

ESPECIALLY RECOMMENDED IN:



All sectors

DESCRIPTION

Audio Splitter Allows 1 line signal to be converted into 10 line outputs with independent volume controls, allowing the output signal level to be adjusted to the input level of the next piece of equipment in the audio chain. All of its inputs and outputs have XLR connectors and are balanced, eliminating the induction noises that can occur on long cable runs. Its simple and intuitive use minimizes setup time depending on the installation. Among its most outstanding uses are press rooms, conference rooms, among others.

TECHNICAL CHARACTERISTICS

FEATURES	Audio splitter with 1 mono input to 10 mono outputs on the front. Independent volume control at each output. Specially for press rooms.
INPUTS	1 balanced line, XLR 215 mV RMS 1 balanced line, XLR 215 mV RMS with 30 cm cable
OUTPUTS	10 balanced lines, XLR 1V RMS maximum
CONTROLS	Volume per output LED power indicator
RESPONSE	20-20,000 Hz
DISTORTION	Harmonic: < 0.2 %
S/N RATIO	> 95 dB
POWER SUPPLY	230/115 V AC, 184 W
DIMENSIONS	484 x 88 x 100 mm depth. 2 U 19" rack
WEIGHT	3.2 kg