

PUBLIC ADDRESS / PUBLIC ADDRESS ACCESSORIES / IMPEDANCE METER

MI-21

IMPEDANCE METER FOR SPEAKER LINES



- ✓ 3 measurement scales
- ✓ Easy-to-read LCD display
- ✓ Easy handling.

ESPECIALLY RECOMMENDED IN:



All sectors

DESCRIPTION

Impedance meter for speakers or low impedance speaker lines, and 100 or 70 V line transformer. An essential tool for PA installation. Allows the speaker line to be checked and measures the resulting impedance.

TECHNICAL CHARACTERISTICS

| | |
|-----------------------------------|--|
| FEATURES | <p>Impedance meter at 1 kHz for loudspeaker lines.</p> <p>Allows the impedance of loudspeaker lines to be checked and the estimated power necessary in a 100 or 70 V line installation, in order to choose the correct amplifier.</p> <p>3 measurement ranges: 200 Ohm, 2 kOhm and 20 kOhm.</p> <p>Easy to read LCD screen.</p> <p>Power meter for 70 and 100 V line loudspeakers.</p> <p>Easy to use.</p> |
| INPUTS | 2 banana plugs to connect the measuring cables. |
| RESOLUTION (MEASUREMENT ACCURACY) | <p>200 Ohm: 0.1 Ohm ($\pm 1\% \pm 2$)</p> <p>2 kOhm: 1 Ohm ($\pm 1\% \pm 2$)</p> <p>20 kOhm: 10 Ohm ($\pm 1\% \pm 2$)</p> |
| POWER SUPPLY | 9 V DC, 1 x 9 V 6LR61 type battery |
| DIMENSIONS | 87x 188 x 38 mm depth |
| WEIGHT | 0.4 kg |
| ACCESSORIES | <p>Rubber protector</p> <p>2 sets of test leads: with alligator clip terminals and precision tips</p> |