

PUBLIC ADDRESS / MIXERS / MONO

## MX-824

MONO MIXER



- ✓ Excellent features
- ✓ Large number of microphone inputs
- ✓ Phantom power supply

ESPECIALLY RECOMMENDED IN:



All sectors

**DESCRIPTION**

12-channel microphone mixer with independent volume control and 48V phantom power supply. The number of microphones in a PA system can easily be increased.

**TECHNICAL CHARACTERISTICS**

FEATURES	Professional 12-channel mixer / preamp. Phantom power.
INPUTS	12 balanced mics, XLR 600 Ohm 2.5 mV
OUTPUTS	1 balanced master XLR 600 Ohm 7 mV and unbalanced 2 x RCA 4,700 Ohm 150 mV
CONTROLS	Volume per master input and output
RESPONSE	50-20,000 Hz
S/N RATIO	> 60 dB
PHANTOM	48 V on mics 1 to 12, selectable
POWER SUPPLY	230/115 V AC, 10 W
DIMENSIONS	483 x 44.5 x 225 mm depth. 1 U 19" rack
WEIGHT	2.7 kg
ACCESSORIES	1 RCA cable 1 XLR cable