

MICROPHONES / FLEXP MICROPHONE / CONDENSER

FCM-752

HIGH DIRECTIVITY HYPERCARDIOID CONDENSER MICROPHONE



- ✓ Crystal clear voice pick-up
- ✓ Adaptable to micro XLR bases
- ✓ Hypercardioid pattern

ESPECIALLY RECOMMENDED IN:



Sports facilities



Centers of
Worship



Hotels



All sectors

DESCRIPTION

Hypercardioid electret condenser microphones for installation or lecterns. Designed to minimize feedback. Wide frequency response. Stylish design with minimum visual impact.

TECHNICAL CHARACTERISTICS

FEATURES	High directivity microphone. Good performance with respect to feedback.
CAPSULE	Hypercardioid electret condenser
RESPONSE	50-16,000 Hz
SENSITIVITY	-34 dB ±3 dB (V/Pa) at 1 kHz
IMPEDANCE	250 Ohm
CONNECTORS	Male XLR Unbalanced line
PHANTOM	48 V DC
SWITCHES	Level: 0 dB/-10 dB Filter: bass/flat cut-off
HEIGHT	Total: 32 cm with gooseneck Adaptable to XLR microphone bases, etc.
COLOUR	White
WEIGHT	0.1 kg
ACCESSORIES	Foam windshield