

SYSTEMS AND CONTROL / VOICE ALARM EN 54 / MODULAR

ZS-4328IO

GENERAL PURPOSE AUDIO INPUT/OUTPUT MANAGEMENT UNIT FOR PUBLIC ADDRESS AND VOICE ALARM SYSTEM EN 54 ZS



- ✔ High reliability
- ✔ Allows up to 4 additional audio sources to be connected to the system

ESPECIALLY RECOMMENDED IN:



All sectors

DESCRIPTION

Audio input management system. General purpose inputs/outputs. Extends the EN 54 PAVA alarm system. It



+ Info:
<https://fonestar.com/ZS-4328IO>

allows the connection of up to 4 additional audio sources to the system. Message player with the capacity to store 512 MB internal memory and 4 GB with the internal SD card. It has 32 general purpose contact opening/closure inputs and 8 outputs.

TECHNICAL CHARACTERISTICS

FEATURES	<p>Audio input management system. General purpose input/outputs. Extends the EN 54 PAVA alarm system. 4 balanced line inputs that transmits over the network to the rest of the system. Message player. 32 supervised contact opening/closure inputs, euroblock. 8 general purpose contact opening/closing outputs, euroblock. 512 MB internal memory and 16 GB memory with internal SD card. 4 ethernet, RJ45. 2 communication ports RS-485.</p> <p>One ZS-4328IO can control and sync 32 ZS-2000M.</p>
POWER SUPPLY	100-240 V AC, 15 W
DIMENSIONS	483 x 92 x 425 mm depth. 2 U 19" rack
WEIGHT	7 kg



+ Info:
<https://fonestar.com/ZS-4328IO>